

# VigorAP 906

2x2 Dual Band WiFi 6 AP

VigorAP 906 is 11ax wall-mount/desktop wireless access point with a 5-port LAN switch. With wire-liked link rate up to 2402 Mbps in 5GHz band and up to 574 Mbps in 2.4GHz band, it's suitable for high density environments. It can be cloud-managed by VigorACS\*, and also act as the mesh Root AP to manage up to 7 mesh node APs in LAN.



# Mesh

Easily link to other VigorAP to expand the wireless network.



PoE Power Supply Simplify the infrastructure by getting data and power through a single cable.



## Airtime Fairness

Equalize the transmission time of each client so the legacy devices won't slow everyone down.



## Multiple SSID

Mapping Wi-Fi clients to different VLANs and have a different set of security standards.



# Assisted Wi-Fi Roaming

Solve the sticky client problem and improve Wi-Fi roaming experience.



# Wi-Fi Scheduling

Schedule Wi-Fi On and Off to control wireless access and save energy.



#### Band Steering Redirect 5GHz-capable devices to the 5GHz radio to get a faster speed.



# Central AP Management

Manage, maintain, and monitor VigorAP 960C from the DrayTek routers.

# AX3000

Delivers link rate up to 3 Gbps

# 254 Users

Acitve at maximum, 127 per radio

# 5 LAN Port

5x 10/100/1000M Base-T RJ-45

# 1 PoE

802.3at compliant

## Interface

LAN Port	5x 10/100/1000M Base-T, RJ-45 (1x PoE)
PoE	802.3at (in)
Antenna	2x External Dipole Dual-Band
	Gain: 2.5 dBi for 5GHz, 2.7 dBi for 2.4GHz
Button	1x Factory Reset
	1x Wireless On/Off/WPS
	1x Power On/Off

#### WLAN

WiFi 6	•
2.4GHz Standard	IEEE 802.11b/g/n/ax 2x2 MIMO,
	up to 1024-QAM
5GHz Standard	IEEE 802.11a/n/ac wave 2/ax 2x2
	MU-MIMO, up to 1024-QAM
2.4GHz Link Rate	Up to 574 Mbps
5GHz Link Rate	Up to 2402 Mbps
Max. Number of Concurrent	254 (127 per radio band)
Active Clients	
Operating Mode	AP, Mesh Root, Mesh Node
Roaming	AP-Assisted Roaming, PMK-Caching,
	Pre-Authentication
AirTime Fairness	Pre-Authentication •
AirTime Fairness Band Steering	Pre-Authentication  •
	Pre-Authentication
Band Steering	Pre-Authentication
Band Steering Auto Channel Selection	Pre-Authentication
Band Steering Auto Channel Selection OFDMA	• • • •
Band Steering Auto Channel Selection OFDMA Max. Number of SSID	• • • •
Band Steering Auto Channel Selection OFDMA Max. Number of SSID WDS	• • • 8 (4 per radio band)
Band Steering Auto Channel Selection OFDMA Max. Number of SSID WDS Client Number Limit	• • • 8 (4 per radio band)

## Application

•
PEAP, EAP-TLS
•
DHCP Server, DHCP, Client,
DHCP Relay Agent
•
•
•
Auto-Reboot, Wi-Fi Up/Down, LED On/Off

#### Management

<u> </u>	
Local Service	HTTP, HTTPS, Telnet
Configuration	Stand Alone, TR-069 (VigorACS),
	Vigor Router APM, VigorAP Mesh Root
Firmware Upgrade	HTTP, TFTP, TR-069
Tools	Speed Test, AP Discovery, Statistics , Interference Monitor
Configuration Backup	
and Restore	•
Syslog	•
Mail Alert	•
SNMP	v1, v2c, v3
Managed by VigorConnect	•
Managed by VigorACS	• *since ACS 3 v3.4.0
Central AP Management	30 VigorAP

### Security

-	
Security Mode	WPA3, WPA3/WPA2, WPA2,
	WPA2/WPA, OWE, WPA, WEP, None
Authentication	Personal, Enterprise
WPS	PIN, PBC
Hidden SSIDs	•
MAC Address Filter	Up to 256 entries
Wireless Client Isolation	•
Mobile Device Management	•

